

B8  
-- Fig. 3 is a view for describing the average bit rate adjusting means 103 shown in Fig. 1;--

Please replace the paragraph beginning on page 23, line 3, with the following rewritten paragraph:

B9  
-- Fig. 3 is a view for describing the average bit rate adjusting means 103 shown in Fig. 1. Referring to the Figure, the average bit rate adjusting means 103 includes an average bit rate virtual buffer occupancy calculator 301 and a quantization step size modifier 302. The virtual buffer occupancy calculator 301 calculates a virtual buffer occupancy from the generated bit count  $S_j$  provided for each GOP from the video coding means 101 and the average bit rate.--

**IN THE CLAIMS:**

Please amend Claims 1, 10, 11, 17, 20 and 21 as follows:

sub  
C1  
1. (Twice amended) An apparatus for variable bit rate video coding of video data on the basis of a predetermined average bit rate comprising:

B10  
a video coding means for coding input video with a predetermined quantization step size and providing coded data and a generated code bit count;

a quantization step size setting means for setting a reference quantization step size for each first image unit, corresponding to an average bit rate, from the predetermined average bit rate, the quantization step size provided to the video coding means and also the generated bit count; and

B10

a quantization step size adjusting means for calculating the average bit rate from the generated bit count and for adjusting the quantization step size provided from the quantization step size setting means for each second image unit from the generated bit count provided from the video coding means and also from a bit balance of the generated bit count with respect to the average bit rate.

c

10. (Twice amended) The apparatus for variable bit rate video coding according to claim 1, wherein:

the quantization step size adjusting means for adjusting the quantization step size for each second image unit preliminarily sets a threshold for quantization step size,

B11

when the bit balance of the generated bit count with respect to the average bit rate is not excessive, the reference quantization step size set for each first image unit is compared with the threshold for quantization step size, for

providing the quantization step size without any adjustment when the reference quantization step size is not exceeding the threshold quantization step size, and

adjusting the quantization step size according to the bit balance to the average bit rate and selectively providing the greater one of the adjusted quantization step size and the threshold for quantization step size, and

when the bit balance of the generated bit count with respect to the average bit rate is excessive, the quantization step size is adjusted according to the bit balance to the average bit rate, the adjusted quantization step size being provided as the quantization step size for each second image unit.

11. (Amended) A method of variable bit rate video coding of video data on the basis of a predetermined average bit rate comprising:

a video coding step of coding input video with a predetermined quantization step size and providing coded data and a generated code bit count;

a quantization step size setting step of setting a reference quantization step size for each first image unit, corresponding to an average bit rate, from the predetermined average bit rate, the quantization step size provided to the video coding step and also the generated code bit count provided therefrom; and

a quantization step size adjusting step of calculating the average bit rate from the generated bit count and of adjusting the quantization step size provided from the quantization step size setting step for each second image unit from the generated code bit count provided from the video coding step and also from a bit balance of the generated bit count with respect to the average bit rate.

17. (Amended) The method of variable bit rate video coding according to claims 11, wherein:

the quantization step size setting step of setting the reference quantization step size for each second image unit includes a step of computing a first quantization step size by adjusting the quantization step size for each second image unit from the generated code bit count provided from the video coding step and the bit balance of the generated bit count with respect to the average bit rate; and

in the computing step, a maximum bit rate is set, a second quantization

B12

step size is computed, which is set in the case of fixed bit rate control on the basis of the maximum bit rate, from the quantization step size set in the quantization step size setting step and the generated code bit count provided from the video coding step, and the greater one of the first and second quantization step sizes is provided to the video coding step.

C

20. (Amended) The method of variable bit rate video coding according to claims 11, wherein:

B13

in the quantization step size adjusting means of adjusting the quantization step size for each second image unit, a threshold quantization step size is preliminarily set, when the bit balance of the generated bit count with respect to the average bit rate is not excessive, the reference quantization step size set for each first image unit is compared with the threshold quantization step size, for providing the quantization step size without any adjustment when the reference quantization step size is not exceeding the bit balance to the average bit rate, and

adjusting the quantization step size according to the bit balance of the generated bit count with respect to average bit rate and selectively providing the greater one of the adjusted quantization step size and the threshold quantization step size, and

when the bit balance of the generated bit count with respect to the average bit rate is excessive, the quantization step size is adjusted according to the bit balance to the average bit rate, the adjusted quantizing with being provided as the quantizing with for each second image unit.